

# We are IntechOpen, the world's leading publisher of Open Access books Built by scientists, for scientists

5,400

Open access books available

133,000

International authors and editors

165M

Downloads

Our authors are among the

154

Countries delivered to

TOP 1%

most cited scientists

12.2%

Contributors from top 500 universities



WEB OF SCIENCE™

Selection of our books indexed in the Book Citation Index  
in Web of Science™ Core Collection (BKCI)

Interested in publishing with us?  
Contact [book.department@intechopen.com](mailto:book.department@intechopen.com)

Numbers displayed above are based on latest data collected.  
For more information visit [www.intechopen.com](http://www.intechopen.com)



## Sensing mechanisms of carbon nanotube based NH<sub>3</sub> gas detectors

Ning Peng\* and Qing Zhang  
*School of Electrical and Electronic Engineering  
Nanyang Technological University  
Singapore*

### 1. Introduction

It is well known that the electrical performance of carbon nanotube (CNT) devices is extremely sensitive to chemical environment. Studying the interaction between CNTs and chemical gases could, from fundamental point of view, significantly deepen our understanding on nanoscale device physics. Meanwhile, as large scale integration of CNT devices is still challenging at the current stage, individual electronic devices containing CNTs as their key elements for sensing purpose would be more feasible for practical applications of CNTs. In addition to a small diameter, an extremely large surface to volume ratio makes CNT a suitable material for nanoscale chemical sensing. Since the first CNT gas sensor reported in 2000 (Kong, et al., 2000), many types of CNT-based chemical sensors have been demonstrated. CNT networks (Li, et al., 2003), functionalized CNTs (Qi, et al., 2003), CNT and polymer composites (Wei, et al., 2006), etc, are used as sensing elements. Although tremendous progresses have been achieved in this area, the underlying sensing mechanism still remains unclear. NH<sub>3</sub> gas detection represents the most typical argument in CNT based gas sensing area. Previously proposed mechanisms include the indirect interaction through the hydroxyl group on SiO<sub>2</sub> substrates (Kong, et al., 2000) or pre-adsorbed water layer (Bradley, et al., 2003), adsorption of gas molecules at the interstitial sites in the CNT bundle (Zhao, et al., 2002), direct charge transfer from the adsorbed gas molecules to the CNT channel (Chang, et al., 2001), and modulation of the SB at CNT/metal contacts (Yamada, 2006), etc. Till now, there is no well recognized sensing mechanisms. Hence in this chapter, we will first review the development of CNT based NH<sub>3</sub> gas sensors. After that, we will present a systematic study on the sensing mechanisms through selective Si<sub>3</sub>N<sub>4</sub> passivation, which enables us to truly distinguish the sensing signal from the CNT channel and CNT/metal contacts. By comparing the strikingly distinct sensing performance at various testing conditions, we clearly show that the Schottky barrier modulation at the CNT/metal contacts dominates the sensing performance at room temperature. At higher temperatures, say 150°C or above, NH<sub>3</sub> molecules start to adsorb on the CNT wall and the charge transfer from the adsorbed NH<sub>3</sub> molecules to the CNTs contributes to the sensing signal. Next, we will demonstrate tunable real-time NH<sub>3</sub> sensors with three-terminal CNT field-effect transistors. The room-temperature sensitivity and reversibility of such sensors can be greatly

enanced by proper gate voltages. Finally, we will conclude the signigance achieved so far and give an outlook of the future development of CNT based gas sensors.

## 2. Literature reviews: Contact Vs Channel

It is well know that most of CNTFETs exhibited p-type characteristics in air, which is commonly attributed the contact SB modulation by environmental oxygen (Derycke, et al., 2002, Heinze, et al., 2002). Will this argument still holds for  $\text{NH}_3$  gas? On one hand, theoretical calculations predicted limited interaction between  $\text{NH}_3$  gas and CNT at room temperature (Kong, et al., 2000, Bauschlicher & Ricca, 2004, Peng & Cho, 1999). On the other hand, CNT based sensors showed high sensitivity to chemical gas. It is natural for researchers to consider the role of metal-CNT contacts. In order to differentiate, or separate the effect from CNT channel and metal-CNT contacts, the design of experiments is to protect or cover either of them and then compare the sensing performance against  $\text{NH}_3$  gas. The first effort belongs to Bradley et al. He and his coworkers used thermally evaporated  $\text{SiO}$  to passivate a short-channel CNTFETs, as shown Fig. 1. They found a good sensitivity to  $\text{NH}_3$  after contact passivation. (Bradley, et al., 2003)




Fig. 1. The device strucutre in Bradley et al's work

Zhang *et al.* argued that when the passivation length was comparable to the depletion length in the CNT, the contacts could be indirectly affected, which could be the case in the work above. In their work, polymethylmethacrylate (PMMA) was applied to protect the CNT/metal contacts from  $\text{NO}_2$  exposure and their devices became insensitive after contact passivation, as shown in Fig. 2. (Zhang, et al., 2006)




Fig. 2. Zhang et al's sensing results after contact passivation.

Interestingly, Liu *et al.* also employed PMMA as a passivation layer. They observed changes in the transfer characteristics upon exposure to NH<sub>3</sub> and NO<sub>2</sub> for both contact-passivated device and channel passivated devices, suggesting that both the CNT channel and the CNT/metal contacts play a role in the detection process (Liu, et al., 2005). The obvious ambiguity in those reports could arise from the permeable passivation materials used. Moreover, as the experiments were carried out at room temperature and air ambient only, exclusive identification of the sensing mechanisms is not possible. Next, we will introduce a selective Si<sub>3</sub>N<sub>4</sub> passivation technique, with which the sensing signals from the CNT channel and CNT/metal contacts are truly distinguished. Strikingly distinct sensing performance at various testing conditions is observed.

### 3. Experimental details

CNTs were aligned between Ti/Au source and drain electrodes predefined on a p-type silicon wafer using an ac DEP technique (Li, et al., 2005, Peng, et al., 2006), which is simple and cost effective, suitable for CNT sensor fabrications. The CNT suspension is introduced onto the electrodes with an AC voltage across with a frequency of 2-10MHz. The peak-to-peak voltage ranged from 6V to 16V, depending on the electrodes separation. Due to the induced DEP force, the CNTs in the suspension align with the electric field direction and move towards the electrodes surface. The AC voltage was turned off immediately once SWNTs bridged the electrodes, confirmed by monitoring the resistance across electrodes. The number of the SWNTs between the electrodes can be controlled by adjusting the SWNT concentration and the manipulation time. A heavily doped Si with a 200 nm thick thermally




Fig. 3. Schematics for (a) Device 1: As-prepared CNTFET; (b) Device 1A: the contacts passivated by Si<sub>3</sub>N<sub>4</sub> and (c) Device 2: the central CNT channel passivated by Si<sub>3</sub>N<sub>4</sub>.

grown  $\text{SiO}_2$  top layer was used as the backgate. Note that the CNTs in this work are on top of Au electrodes and the contact regions are fully accessible to the ambient. These devices are typically the SB-CNTFETs. As illustrated in Fig. 3, three device structures were employed in our experiments: (1) an as-prepared CNTFET with the exposed CNT channel and CNT/Au contacts; (2) only the contacts passivated with 500nm  $\text{Si}_3\text{N}_4$  layer and (3) only the channel passivated with 500nm  $\text{Si}_3\text{N}_4$  layer. Dry air was used as the background gas with a flow rate of 500sccm in the following experiments unless otherwise stated.  $\text{NH}_3$  gas was selected as the detecting species to study the sensing mechanisms of the CNT sensors.

## 4. Results and Discussion

### 4.1 $\text{NH}_3$ sensing at room-temperature

An as-prepared CNTFET (Device 1) showed a sensitive response to small concentrations of  $\text{NH}_3$  at room temperature (see Fig.4 (a)). It is seen that, under a positive gate voltage, both the sensitivity and reversibility were much higher than those under a negative one.




Fig. 4. Real-time detection of  $\text{NH}_3$  at room temperature under various gate voltages (a) before (Device 1) and (b) after the contacts passivation (Device 1A), respectively. Inset: an atomic force microscope (AFM) image of Device 1A after the passivation.

In order to experimentally differentiate whether the sensing responses are from the CNT channel and/or the CNT/Au contacts, we passivated the CNT/Au contacts of Device 1 with a Si<sub>3</sub>N<sub>4</sub> thin film, leaving the CNT channel open. After the passivation, we found that the device (Device 1A) did not respond to NH<sub>3</sub> at room temperature, even at a concentration up to 500ppm, as shown in Fig. 4 (b). For comparison, we only passivated the CNT channel with Si<sub>3</sub>N<sub>4</sub> thin film in another CNTFET (Device 2), but uncovering the CNT/Au contacts. Interestingly, Device 2 showed a high sensitivity at room temperature (see Fig. 5). Therefore, we can unambiguously conclude that NH<sub>3</sub> gas induced SB modulation is a dominant mechanism for our CNT gas sensors at room temperature.




Fig. 5. Sensing response of Device 2 at room temperature. Inset: AFM image of Device 2 with central channel passivated.

Actually, PMMA was widely employed as a passivation material to protect the CNT/metal contact regions for gas (Zhang, et al., 2006, Liu, et al., 2005) and protein sensing (Heller, et al., 2008). However, two major problems exist due to the polymer nature of PMMA. Firstly, PMMA is not dense enough to fully passivate the contacts. For example, NO<sub>2</sub> was found to penetrate the 2.2μm thick SU-8/PMMA layer in 30mins (Zhang, et al., 2006). Thus, the CNT/metal contacts are inevitably affected by the gradual diffusion of the detecting species through the PMMA layer, so that the role of the contact in the detection could not be eliminated. Secondly, PMMA is thermally unstable above 100°C. This is a critical limitation as the adsorptions of some biomolecules and gas molecules on CNTs are enhanced at high temperatures. In contrast, Si<sub>3</sub>N<sub>4</sub> is much denser and it can completely insulate the contacts from chemical environment (Kaminishi, et al., 2005). Meanwhile, its thermal stability allows for high temperature sensing experiments, as shown later.

#### 4.2 NH<sub>3</sub> sensing at elevated temperature

The transfer curves of Device 1A before and after exposure to 500ppm NH<sub>3</sub> for 1000s are monitored at T=25°C, T=50°C and T=100°C in Fig. 6 (a), (b) and (c), respectively. No

significant change in  $V_{TH}$  curves was observed. We suggest that, the adsorption of  $NH_3$  on the CNT is not favored at this temperature range.




Fig. 6. Transfer characteristics of Device 1A with contacts passivated before and after exposure to  $NH_3$  at (a)  $T=25^\circ C$ , (b)  $T=50^\circ C$  and (c)  $T=100^\circ C$  respectively.




Fig. 7. The transfer characteristics for Device 1A with the contacts passivated before and after exposure to NH<sub>3</sub> at (a) T=150°C and (b) T=200°C, respectively.

The transfer curve started to shift towards negative gate voltage after NH<sub>3</sub> exposure at 150°C and above, see Fig. 7 (a). Since the contacts were fully isolated from NH<sub>3</sub>, this parallel shift in the transfer curve suggests that NH<sub>3</sub> could adsorb on the CNT wall and donate electrons to the CNT. Consequently, the Fermi level of the CNT moves towards the conduction band edge so that the threshold voltage  $V_{TH}$  becomes more negative. When the testing temperature reached 200°C, this phenomenon became more prominent. Progressive shift of the transfer curve in accordance with NH<sub>3</sub> concentrations is shown in Fig. 7 (b).

Under a first order estimation, the total charge transferred  $\Delta Q = C_G \Delta V_{TH}$ , where the gate

capacitance  $C_G = \frac{2\pi\epsilon\epsilon_0 L}{\cosh^{-1}(h/r)}$ , the SiO<sub>2</sub> dielectric constant  $\epsilon=3.9$  and thickness  $h=200\text{nm}$ .

For a SWNT bundle with a length  $L\sim 5\mu\text{m}$  and a radius  $r\sim 5\text{nm}$ ,  $C_G\approx 0.25\text{fF}$ . Thus,  $\Delta Q$  is approximately  $0.625\text{fC}$  or about 4000 electrons, at  $200^\circ\text{C}$  with  $\Delta V_{TH} = 2.5\text{V}$  for 500ppm NH<sub>3</sub>. If the cross-sectional area of NH<sub>3</sub>  $A\sim 0.13\text{nm}^2$ , the length of the exposed CNT channel  $L'\sim 3\mu\text{m}$ , the coverage  $\theta\sim 0.07$  (interpolated from the Langmuir plot for 500ppm NH<sub>3</sub> on CNT(Bradley, et al., 2003)), the charge transfer rate  $f \approx \Delta Q A / q \theta \pi r L'$  is about 0.02 electron. This value is reasonably consistent with typical theoretical predictions.




Fig. 8. Extracted sensitivities for (a) Device 1 and Device 1A at  $T=25^\circ\text{C}$ ; (b) Device 2 and Device 1A at  $T=150^\circ\text{C}$ , respectively.

The extracted sensitivity  $S = \Delta R / R_0$  of Device 1 and Device 1A under three gate voltages at T=25°C are shown in Fig. 8 (a). For Device 1, a very high sensitivity and significant gate modulation were observed. When the gate voltage is varied from negative to positive, the dominant carrier injection process changes from tunneling to thermionic emission, and the source-drain current becomes very sensitive to the SB height. A small change in the contact SB height due to NH<sub>3</sub> adsorption will be prominently reflected in the source-drain current. Our device structure with a CNT on top of metal electrodes could also enhance the SB modulation effect. Once the contacts passivation is carried out in Device 1A, it essentially does not respond to NH<sub>3</sub>, implying that the CNT channel is not active to NH<sub>3</sub> at room temperature. Fig. 8 (b) compares the sensitivities for Device 1A and Device 2 at T=150°C. At small NH<sub>3</sub> concentrations, a low coverage of NH<sub>3</sub> on the CNT channel and poor charge transfer efficiency result in a small sensitivity in Device 1A. When the NH<sub>3</sub> concentration is increased, the sensitivity for Device 2 becomes saturated, probably due to limited interaction area in the CNT/Au contacts.

#### 4.3 Effect of oxygen on NH<sub>3</sub> sensing

Theoretical studies suggest that, NH<sub>3</sub> interacts weakly with pristine CNTs with little charge transfer (Kong, et al., 2000, Bauschlicher & Ricca, 2004, Peng & Cho, 1999). Existence of a large activation barrier prevents adsorption of NH<sub>3</sub> on perfect CNTs even at high temperatures. However, the adsorption of the gas molecules on defective CNTs could be much easier (Feng, et al., 2005, Robinson, et al., 2007). In addition, the adsorption barrier of NH<sub>3</sub> on a defective CNT can be further lowered by pre-dissociated oxygen atoms, leading to an enhanced charge transfer rate, as pointed out by Andzelm et al (Andzelm, et al., 2006). In order to study the influences of oxygen on NH<sub>3</sub> adsorption onto the CNT wall, we changed the background gas from dry air to N<sub>2</sub>. Device 1A was first annealed in N<sub>2</sub> environment at 350°C for 2 hrs to degas the adsorbed oxygen. Note that during the high-temperature annealing, remaining oxygen molecules at the contacts can be further desorbed and the device became more n-type. The transfer curves before and after exposure to 500ppm NH<sub>3</sub> for 1000s from T=25°C to T=150°C were shown in Fig. 9, and real-time sensing results at T=200°C are shown in Fig. 10. No detectable changes due to NH<sub>3</sub> exposure were observed. Comparing with the sensing response observed in dry air environment, we can confirm that the adsorption of NH<sub>3</sub> is facilitated by environmental oxygen. It was also found that the sensitivity was restored after the background was changed to dry air again. Our results are consistent with Andzelm *et al's* predictions. NH<sub>3</sub> could preferentially attach to the defect sites on CNT with pre-dissociated oxygen, as illustrated in Fig. 11.




Fig. 9. Transfer characteristics of Device 1A in  $N_2$  before and after exposure to  $NH_3$  at (a)  $T=25^\circ C$ , (b)  $T=50^\circ C$ , (c)  $T=100^\circ C$  and (d)  $T=150^\circ C$  respectively.




Fig. 10. Response of  $I_{SD}$  to various concentrations of  $NH_3$  in  $N_2$  at  $T=200^\circ C$  for Device 1A.




Fig. 11. Schematic of NH<sub>3</sub> adsorption on Device 1A. Here, we illustrate a NH<sub>3</sub> molecule adsorbs on a CNT with Stone-Wales defect with pre-dissociated oxygen atoms, as suggested in by Andzelm et al.

#### 4.4 Comparisons of the sensing mechanisms in CNT based gas sensors

From our results, we are able to rule out several possibilities of indirect interactions between NH<sub>3</sub> and CNT. Firstly, as the testing environment was totally dry, NH<sub>3</sub> adsorption through water layer is not applicable here. Secondly, If NH<sub>3</sub> could interact through the SiO<sub>2</sub> substrate or adsorb inside the CNT bundles, a reduced sensitivity should have been observed after contacts passivation. However, our observation that Device 1A is totally insensitive to NH<sub>3</sub> at room temperature does not support this hypothesis. In fact, charge transfer and the SB modulation are the two mechanisms in our CNT sensors.

At room temperature, the weak adsorption of NH<sub>3</sub> on the CNT wall does not induce any measurable effect on the source-drain current. The sensing signal mainly arises from the contacts. When NH<sub>3</sub> molecules are adsorbed on the CNT/Au interface, the work function of the Au electrode is reduced (Bilic, et al., 2002) and/or the electrostatic charge balance between the CNT and Au is disturbed by the dipoles of NH<sub>3</sub> molecules, (Yamada, 2006) leading to an increased SB for hole injection. The sensitivity reflected in the source-drain current are, however, gate voltage dependant. As illustrated in Figure 12 (b), when a negative gate voltage bends the energy band of the CNT upwards, the SB width becomes very narrow and holes could tunnel through the barrier, even when the SB height is increased by NH<sub>3</sub>. In contrast, at a positive gate voltage, the SB width is too thick for tunneling process. Thus, hole injection is only through thermionic emission over the SB height. The source-drain current is then expressed as: (Appenzeller, et al., 2004)  $I_{DS} \sim T^2 \exp(-q\phi_B / K_B T)$ , where  $\phi_B$  is the Schottky barrier height,  $K_B$  is the

Boltzmann's constant and  $T$  is the temperature in Kelvin. In this case, the sensitivity for the SB modulation is  $S = \Delta R / R_0 \approx \exp(q\Delta\phi_B / K_B T) - 1$ . Owing to the exponential dependence on the SB height change  $\Delta\phi_B$ , extremely high sensitivity can be achieved. Our results are consistent with Yamada's theoretical prediction that the SB modulation is most significant when CNT is operating in the depletion mode. (Yamada, 2006)

One disadvantage of the SB dominated sensors is a typical long recovery process at room temperature. Once the operating temperature is increased, the sensitivity degrades sharply due to its exponential dependence with  $1/T$ . The nanoscale CNT/metal contacts could also be prone to subtle environmental noises, causing fluctuations during detection. In contrast, using the CNT channel as a sensing element can avoid the problems. In addition, the large surface to volume ratio of CNT offers another merit. At  $T > 150^\circ\text{C}$ , when the adsorption barrier is further lowered by oxygen,  $\text{NH}_3$  adsorption on the defect sites of the CNT becomes favored. Upon the consequent charge transfer, the Fermi level of the exposed central CNT channel moves upwards and the energy band shifts downwards with respect to those passivated parts, a potential barrier is therefore created and impedes the current flow, see Fig. 12 (d). Here, we would like to emphasize that, the charge transfer effect can be studied only when the contacts are fully protected. Otherwise, as temperature increases, the sensitivity enhancement from the charge transfer effect and the degradation due to SB modulation counteract each other.




Fig. 12. Schematic energy band diagram for: Device 1 (a) before and (b) after the  $\text{NH}_3$  exposure (An intrinsic CNT is considered. The work function of the source/drain electrodes is initially near the valence band edge of the CNT and is reduced after  $\text{NH}_3$  exposure); Device 1A (c) before and (d) after the  $\text{NH}_3$  exposure (After passivation, the work function of electrodes aligns near the midgap of CNT. The Fermi level of the exposed central CNT channel shifts upwards due to electron-doping from  $\text{NH}_3$ ). Legend: Red dotted for  $V_{\text{GS}} < 0$ ; Green solid for  $V_{\text{GS}} = 0$ ; Blue dashed for  $V_{\text{GS}} > 0$ .

Table 1 compares the SB modulation and charge transfer mechanisms. The sensors with the SB modulation usually demonstrate a high sensitivity at room temperature. Their sensing performance can be adjusted through the gate voltages. In contrast, the sensors under the charge transfer mechanism require high working temperatures, showing a good reversibility.

<b>Mechanism</b>	<b>SB modulation</b>	<b>Charge transfer</b>
<b>Sensitivity</b>	<b>Extremely high in depletion mode</b>	<b>Low</b>
<b>Gate dependence</b>	<b>Strong</b>	<b>Weak</b>
<b>Operating Temperature</b>	<b>Room temperature</b>	<b>T&gt;150°C</b>
<b>Reversibility</b>	<b>Low, can be improved at positive gate voltage</b>	<b>Good</b>

Table 1. Comparisons between sensors operated by SB modulation and charge transfer.

## 5. Conclusions and Future Work

In this chapter, we discussed in details the sensing mechanisms of CNT based NH<sub>3</sub> detection. By selective Si<sub>3</sub>N<sub>4</sub> passivation, We clearly show that the SB modulation at the CNT/metal contacts dominates the sensing performance at room temperature, and the sensor exhibits high sensitivity and good tunability under appropriate gate voltages. At higher temperatures, say 150°C or above, NH<sub>3</sub> molecules start to adsorb on the CNT wall and the charge transfer process from the adsorbed NH<sub>3</sub> molecules to the CNTs contributes to the sensing signal. As the mechanisms are identified, the next step is how to improve the sensing performance, and more challengingly, how to differentiate between different gas species. One promising way could be functionalization method (Feng, et al., 2005, Qi, et al., 2003). For example, using metal catalysts in the form of nanoparticles to decorate CNT, which promotes the interaction with specific gas species. With a combination of several metal nanoparticles, the sensing performance to various gas molecules could be compared and contrasted.

## 6. Reference

- Andzelm, J.; Govind, N. & Maiti, A. (2006). Nanotube-based gas sensors - Role of structural defects. *Chemical Physics Letters*, Vol. 421, No. 1-3: 58-62, 0009-2614
- Appenzeller, J.; Radosavljevic, M.; Knoch, J. & Avouris, P. (2004). Tunneling versus thermionic emission in one-dimensional semiconductors. *Physical Review Letters*, Vol. 92, No. 4, 0031-9007


- Bauschlicher, C. W. & Ricca, A. (2004). Binding of NH<sub>3</sub> to graphite and to a (9,0) carbon nanotube. *Physical Review B*, Vol. 70, No. 11, 1098-0121
- Bilic, A.; Reimers, J. R.; Hush, N. S. & Hafner, J. (2002). Adsorption of ammonia on the gold(111) surface. *Journal of Chemical Physics*, Vol. 116, No. 20: 8981-8987, 0021-9606
- Bradley, K.; Gabriel, J. C. P.; Briman, M.; Star, A. & Gruner, G. (2003). Charge transfer from ammonia physisorbed on nanotubes. *Physical Review Letters*, Vol. 91, No. 21, 0031-9007
- Bradley, K.; Gabriel, J. C. P.; Star, A. & Gruner, G. (2003). Short-channel effects in contact-passivated nanotube chemical sensors. *Applied Physics Letters*, Vol. 83, No. 18: 3821-3823, 0003-6951
- Chang, H.; Lee, J. D.; Lee, S. M. & Lee, Y. H. (2001). Adsorption of NH<sub>3</sub> and NO<sub>2</sub> molecules on carbon nanotubes. *Applied Physics Letters*, Vol. 79, No. 23: 3863-3865, 0003-6951
- Derycke, V.; Martel, R.; Appenzeller, J. & Avouris, P. (2002). Controlling doping and carrier injection in carbon nanotube transistors. *Applied Physics Letters*, Vol. 80, No. 15: 2773-2775, 0003-6951
- Feng, X.; Irlle, S.; Witek, H.; Morokuma, K.; Vidic, R. & Borguet, E. (2005). Sensitivity of ammonia interaction with single-walled carbon nanotube bundles to the presence of defect sites and functionalities. *Journal of the American Chemical Society*, Vol. 127, No. 30: 10533-10538, 0002-7863
- Heinze, S.; Tersoff, J.; Martel, R.; Derycke, V.; Appenzeller, J. & Avouris, P. (2002). Carbon nanotubes as Schottky barrier transistors. *Physical Review Letters*, Vol. 89, No. 10, 0031-9007
- Heller, I.; Janssens, A. M.; Mannik, J.; Minot, E. D.; Lemay, S. G. & Dekker, C. (2008). Identifying the mechanism of biosensing with carbon nanotube transistors. *Nano Letters*, Vol. 8, No. 2: 591-595, 1530-6984
- Kaminishi, D.; Ozaki, H.; Ohno, Y.; Maehashi, K.; Inoue, K.; Matsumoto, K.; Seri, Y.; Masuda, A. & Matsumura, H. (2005). Air-stable n-type carbon nanotube field-effect transistors with Si<sub>3</sub>N<sub>4</sub> passivation films fabricated by catalytic chemical vapor deposition. *Applied Physics Letters*, Vol. 86, No. 11, 0003-6951
- Kong, J.; Franklin, N. R.; Zhou, C. W.; Chapline, M. G.; Peng, S.; Cho, K. J. & Dai, H. J. (2000). Nanotube molecular wires as chemical sensors. *Science*, Vol. 287, No. 5453: 622-625, 0036-8075
- Li, J. Q.; Zhang, Q.; Peng, N. & Zhu, Q. (2005). Manipulation of carbon nanotubes using AC dielectrophoresis. *Applied Physics Letters*, Vol. 86, No. 15, 0003-6951
- Li, J.; Lu, Y. J.; Ye, Q.; Cinke, M.; Han, J. & Meyyappan, M. (2003). Carbon nanotube sensors for gas and organic vapor detection. *Nano Letters*, Vol. 3, No. 7: 929-933, 1530-6984
- Liu, X. L.; Luo, Z. C.; Han, S.; Tang, T.; Zhang, D. H. & Zhou, C. W. (2005). Band engineering of carbon nanotube field-effect transistors via selected area chemical gating. *Applied Physics Letters*, Vol. 86, No. 24, 0003-6951
- Peng, N.; Zhang, Q.; Li, J. Q. & Liu, N. Y. (2006). Influences of ac electric field on the spatial distribution of carbon nanotubes formed between electrodes. *Journal of Applied Physics*, Vol. 100, No. 2, 0021-8979
- Peng, S. & Cho, K. J. (1999). Chemical control of nanotube electronics. *7th Annual Foresight Conference on Molecular Nanotechnology*, 57-60, Santa Clara, California.

- Qi, P.; Vermesh, O.; Grecu, M.; Javey, A.; Wang, O.; Dai, H. J.; Peng, S. & Cho, K. J. (2003). Toward large arrays of multiplex functionalized carbon nanotube sensors for highly sensitive and selective molecular detection. *Nano Letters*, Vol. 3, No. 3: 347-351, 1530-6984
- Robinson, J. A.; Snow, E. S. & Perkins, F. K. (2007). Improved chemical detection using single-walled carbon nanotube network capacitors. *Sensors and Actuators a-Physical*, Vol. 135, No. 2: 309-314, 0924-4247
- Wei, C.; Dai, L. M.; Roy, A. & Tolle, T. B. (2006). Multifunctional chemical vapor sensors of aligned carbon nanotube and polymer composites. *Journal of the American Chemical Society*, Vol. 128, No. 5: 1412-1413, 0002-7863
- Yamada, T. (2006). Equivalent circuit model for carbon nanotube Schottky barrier: Influence of neutral polarized gas molecules. *Applied Physics Letters*, Vol. 88, No. 8, 0003-6951
- Yamada, T. (2006). Equivalent circuit model for carbon nanotube Schottky barrier: Influence of neutral polarized gas molecules. *Applied Physics Letters*, Vol. 88, No. 8: 083106, 0003-6951
- Zhang, J.; Boyd, A.; Tselev, A.; Paranjape, M. & Barbara, P. (2006). Mechanism of NO<sub>2</sub> detection in carbon nanotube field effect transistor chemical sensors. *Applied Physics Letters*, Vol. 88, No. 12, 0003-6951
- Zhao, J. J.; Buldum, A.; Han, J. & Lu, J. P. (2002). Gas molecule adsorption in carbon nanotubes and nanotube bundles. *Nanotechnology*, Vol. 13, No. 2: 195-200, 0957-4484

IntechOpen

IntechOpen

IntechOpen



## **Carbon Nanotubes**

Edited by Jose Mauricio Marulanda

ISBN 978-953-307-054-4

Hard cover, 766 pages

**Publisher** InTech

**Published online** 01, March, 2010

**Published in print edition** March, 2010

This book has been outlined as follows: A review on the literature and increasing research interests in the field of carbon nanotubes. Fabrication techniques followed by an analysis on the physical properties of carbon nanotubes. The device physics of implemented carbon nanotubes applications along with proposed models in an effort to describe their behavior in circuits and interconnects. And ultimately, the book pursues a significant amount of work in applications of carbon nanotubes in sensors, nanoparticles and nanostructures, and biotechnology. Readers of this book should have a strong background on physical electronics and semiconductor device physics. Philanthropists and readers with strong background in quantum transport physics and semiconductors materials could definitely benefit from the results presented in the chapters of this book. Especially, those with research interests in the areas of nanoparticles and nanotechnology.

### **How to reference**

In order to correctly reference this scholarly work, feel free to copy and paste the following:

Ning Peng and Qing Zhang (2010). Sensing Mechanisms of Carbon Nanotube Based NH<sub>3</sub> Gas Detectors, Carbon Nanotubes, Jose Mauricio Marulanda (Ed.), ISBN: 978-953-307-054-4, InTech, Available from: <http://www.intechopen.com/books/carbon-nanotubes/sensing-mechanisms-of-carbon-nanotube-based-nh3-gas-detectors>

**INTECH**  
open science | open minds

### **InTech Europe**

University Campus STeP Ri  
Slavka Krautzeka 83/A  
51000 Rijeka, Croatia  
Phone: +385 (51) 770 447  
Fax: +385 (51) 686 166  
[www.intechopen.com](http://www.intechopen.com)

### **InTech China**

Unit 405, Office Block, Hotel Equatorial Shanghai  
No.65, Yan An Road (West), Shanghai, 200040, China  
中国上海市延安西路65号上海国际贵都大饭店办公楼405单元  
Phone: +86-21-62489820  
Fax: +86-21-62489821

© 2010 The Author(s). Licensee IntechOpen. This chapter is distributed under the terms of the [Creative Commons Attribution-NonCommercial-ShareAlike-3.0 License](#), which permits use, distribution and reproduction for non-commercial purposes, provided the original is properly cited and derivative works building on this content are distributed under the same license.

IntechOpen

IntechOpen